

SERIES BM1000

BM1000P TOP






WEIGHT	1,5 kg
DIMENSIONS	23 X 18 X 22 cm
PACKING VOLUME	0,009 m³

GROUP

SERIES BM1000

BM1000P TOP

CHARACTERISTICS	MODEL	REFERENCE
<ul style="list-style-type: none">6-digit 25 mm high LCD display with backlighting.28-key multifunction keyboard.999 programmable items with: Article name 24 characters; Item tare; Unit Weight.Tare fixing.Programmable tare.Automatic or manual tare reset.Weight-tare function and count pieces with: Printing of tickets; Printing of labels; 2 programmable header lines with 16 characters.2 RS 232 communication ports.Real time clock.Power supply 220 V.Connection to a second platform (to any one of the range of platforms Marques) <p>Model Relays (I/O)</p> <ul style="list-style-type: none">4 Solid State Relay outputs.<ul style="list-style-type: none">Up to 230V AC/DC and 100mA driving capability;Can be configured as OFF, NO, NC or timed Pulse;Action triggered by weight value.4 Opto Isolated Inputs.<ul style="list-style-type: none">Up to 30V DC input levels.4-20mA Current Loop.<ul style="list-style-type: none">Independent Min and Max freely defined by weight values at setup;Min and Max levels fine tune at setup.	BM1000P TOP	20433450200J
	BM1000P TOP BAT	20433450300J
	BM1000P TOP AC	20433450000J
	BM1000P TOP AC BAT	20433450100J
	BM1000P TOP AC RELÉS	20433450012J
OPTIONS		REFERENCE
Ethernet + Wifi		20756020000A
RGB Levels LED		20709210000A
Siren warning sound		20765010000A
Swivel wall bracket		20716240000B

2021 | V.1 - Prohibited Reproduction / Specifications subject to change without prior notice

See the price list



www.balancasmарques.com
facebook.com/balancasmарques

HEAD OFFICE

Edifício Balanças Marques
Parque Industrial de Celeirós, 2ª Fase
Apart. 2376
4701-905 Braga - PORTUGAL

LISBON SUPPORT CENTER

Rua Actriz Adelina Fernandes 15A Dto.
2795-005 Linda-a-Velha
Lisboa - PORTUGAL

T +351 253 309 830
F +351 253 672 882
email internacional@balancasmарques.pt